

HV High-Power CDN for EFT/Burst and Surge Immunity Tests

SEPN 6932T

Datasheet



In Compliance with

- > IEC/EN 61000-4-4
- > IEC/EN 61000-4-5
- > IEC 61000-6-1
- > IEC 61000-6-2
- > GB/T 17626.4
- > GB/T 17626.5

Introduction

The SEPN 6932T three-phase automatic coupling/decoupling network for EFT/Burst and surge immunity tests is designed according to test requirements of IEC/EN 61000-4-4 and IEC/EN 61000-4-5, features stable performance and convenient operation. The device is used together with CCS series, CWS series and EFT series of 3ctest. It can couple surge and EFT/Burst wave pulses onto three-phase mains supply system with voltage AC 690 V and current 32 A and can also be customized according to actual EUT load.

Features

- > EUT load capacity AC 690 V, 32 A, 3-phase 5-wire;
- > Automatic switching with scheduling of test voltages, polarities, phases and angles;
- > Current detection, over-current protection;
- > Superposition of any lines with any phases and angles;

Application Areas

- | | |
|-------------------|-------------------------------|
| > Communication | > IT |
| > Telecom | > Military |
| > Medical | > Avionics |
| > TV Broadcasting | > New energy electrical power |
| > Railway | |

Technical Parameters – EFT/Burst	
3-Phase Automatic CDN	(As per IEC/EN 61000-4-4) Max. test voltage: 4.2 kV (Note: the actual output voltage is subject to the set value of the generator)
Phase Sync	Any combination of L1, L2, L3, N, PE with any phases and angles
Coupling Paths	Any combination of L1, L2, L3, N, PE
Switching of Coupling Paths	Automatic as per scheduled
Coupling Capacitance	33 nF
Coupling Attenuation	<2 dB
Residue Impulse Voltage at EUT Input End	≤ 10% of test voltage;


General Parameters	
EUT Load Capacity	Max AC 690V, 32 A, 50/60 Hz, 3-phase 5-wire;
Switching Method of EUT Power Supply	Automatic
Short-term Inrush Current	Peak value 400 A
Current Detection	Front panel co-axial terminal output: 100 A: 1 V
Over-current Protection	Alarm limit: rated current x 1.5; When ms-level continuous over-current is reached, warn information will displayed on LCD screen and EUT circuit will be cut off.
Operating Power Supply	AC 110V / 220 V ±10%, 50/60 Hz ± 5%
Fuse	6 A
Max Power	200 W
Auxiliary Port	D- sub 25p
Operating Status	Front panel LED indicators
Grounding Method	Flat grounding strap
Dimension	19"/22 U
Weight	About 200 kg
Ambient Temperature	15°C~35°C
Relative Humidity	45% ~ 75%
Atmospheric Pressure	86 kPa ~ 106 kPa

Technical Parameters - Surge	
3-Phase Automatic CDN	As per IEC/EN 61000-4-5, Max test voltage: 8 kV (1.2/50 µs), max. test current: 4 kA (8/20 µs) (Note: the actual output voltage is subject to the set value of the generator)
Phase Sync	Any combination of L1, L2, L3, N, PE with any phases and angles
Coupling Paths	Any combination of L1, L2, L3, N, PE
Switching of Coupling Paths	Automatic as per scheduled
Coupling Capacitance	9 nF, 18 nF
Coupling Resistance	10 Ω, 0Ω (standard or user-defined)
Coupling Attenuation	<2 dB
Residual Impulse Voltage at EUT Input Terminal	≤ 15% of test voltage or 2 times of rated peak voltage of CDN;

Accessories	
User manual, Test line, 3-core Power line, Grounding line, Fuse (spare parts), Coaxial cable	

Optional Generators & Calibration Tools	
EFT 500x	EFT/Burst generator, as per IEC 61000-4-4, max. burst output voltage 4.8 kV
EFT 600x	EFT/Burst generator, as per IEC 61000-4-4, max. burst output voltage 6.0 kV
EFT 500x	EFT/Burst generator, as per IEC 61000-4-4, max. burst output voltage 7.0 kV
CWS 600x	Surge generator; as per IEC 61000-4-5; max. pulse output voltage 6.0 kV (1.2/50 µs), output current 3.0 kA (8/20 µs)
CWS 800x	Surge generator; as per IEC 61000-4-5; max. pulse output voltage 8.0 kV (1.2/50 µs), output current 4.0 kA (8/20 µs)
CWS 1000x	Surge generator; as per IEC 61000-4-5; max. pulse output voltage 10.0 kV (1.2/50 µs), output current 5.0 kA (8/20 µs)
CCS 600x	Surge and EFT/Burst generator; As per IEC 61000-4-4, max burst output voltage is 4.8 kV As per IEC 61000-4-5, max. pulse output voltage 6.0 kV (1.2/50 µs), output current 3.0 kA (8/20 µs)
CCS 1000x	Surge and EFT/Burst generator; As per IEC 61000-4-4, max burst output voltage is 4.8 kV As per IEC 61000-4-5, max. pulse output voltage 10.0 kV (1.2/50 µs), output current 5.0 kA (8/20 µs)
VCF-80	HV differential probe, for calibration of Surge generator (open-circuit voltage waveform); test voltage max 8 kV, attenuation: 1000:1;
TR 5025	HV current transducer, for calibration of Surge generator (short-circuit current waveform); Test current max 20 kA, attenuation 100:1;
Calibration Kit for EFT/Burst Generators	TFB 50: input impedance 50 Ω, output impedance 50 Ω, attenuation 55 dB; TFB 1000: input impedance 1000 Ω, output impedance 50 Ω, attenuation 60 dB; Supplied with network adaptors and tool box.

Naming Rules





苏州泰思特电子科技有限公司

地址：江苏省苏州市科技城峨眉山路99号 电话：0512-68413700 / 68413800 / 68413900

客服热线：4006-0512-77 售后电话：0512-68078090 售后邮箱：service@3ctest.cn

公司官网：www.3ctest.cn E-mail：info@3ctest.cn

北京办事处

地址：北京市海淀区丰慧中路7号新材料创业大厦B座205室
电话：010-82899948 010-82899984

成都办事处

地址：成都市高新区天益街38号(地铁高新站出口)
理想中心3栋1501室
电话：028-65772800 028-85327800

深圳办事处

地址：深圳市南山区西丽茶光路华文大厦805室
电话：0755-86626661 86344313 86626625

西安办事处

地址：西安市雁塔区高新六路立人科技园A座409室
电话：029-68985077

